

Celadon Inc.
RCV-5000 IR to RS-232 Output Table
Device: EXTRON SW6 SV A MX Switcher

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol
 Infrared Code Format: NEC - Device ID: 7B02
 Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description
 Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver
 RCV-5000 Data File: extron1_r.hex
 Data: 9600 Baud, 8, N, 1, ASCII Output
 Standard Transmit and Receive pinout

Extron Function	Pronto Button	RCV-5000 Output
Select Video/Audio Input	0	1!
Select Video/Audio Input	1	2!
Select Video/Audio Input	2	3!
Select Video/Audio Input	3	4!
Select Video/Audio Input	4	5!
Select Video/Audio Input	5	6!
Select Audio Input Only	6	1\$
Select Audio Input Only	7	2\$
Select Audio Input Only	8	3\$
Select Audio Input Only	9	4\$
Select Audio Input Only	10	5\$
Select Audio Input Only	11	6\$
Select Video Input Only	12	1&
Select Video Input Only	13	2&
Select Video Input Only	14	3&
Select Video Input Only	15	4&
Select Video Input Only	16	5&
Select Video Input Only	17	6&

Celadon, Inc.
 50 Mitchell Blvd.
 San Rafael, CA 94903
 Tel: (415) 472-1177
 Fax: (415) 472-1179
 sales@celadon.com